

### Elektromos adatok

#### Minősítés az IEC/EN 60664-1 szerint

Névleges feszültség (III / 3)	800 V
Névleges áram	57 A

#### Robbanásvédelmi információk

Névleges áram (Ex e II)	50 A
-------------------------	------

### Fizikai adatok

Szélesség	47,6 mm / 1.874 inch
Magasság	4,1 mm / 0.161 inch
Mélység	23 mm / 0.906 inch
Cellaáthidaló osztása	5 ágú

### Anyag információk

Note (material data)	<a href="#">Information on material data can be found here</a>
Szín	világosszürke
Tűzterhelés	0.041 MJ
Tömeg	10 g

### Kereskedelmi adatok

Product Group	22 (TOPJOB S)
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 8.0	EC000489
ETIM 7.0	EC000489
Csomagolási egység	25 Stück
Csomagolás típusa	Bag
Származási ország	DE
EAN/VTSZ	4055143701990
Vámtarifaszám	85366990990

**Letöltések**

**Environmental Product Compliance**

Compliance Search	
Environmental Product Compliance 2010-405	<a href="#">↓</a>

**Documentation**

Additional Information		
Technical Section	pdf 2142.18 KB	<a href="#">↓</a>

Bid Text			
2010-405	19.02.2019	xml 2.51 KB	<a href="#">↓</a>
2010-405	28.04.2017	doc 23.50 KB	<a href="#">↓</a>



**CAD/CAE-Data**

CAD data	
2D/3D Models 2010-405	<a href="#">↓</a>

CAE data	
EPLAN Data Portal 2010-405	<a href="#">↓</a>
WSCAD Universe 2010-405	<a href="#">↓</a>
ZUKEN Portal 2010-405	<a href="#">↓</a>

**Szerelési útmutató**



**Összekötés**



Insert push-in type jumper bar and push down until it hits backstop.

Removing a push-in type jumper bar: Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper. Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

**Összekötés**




Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).

Marking with a felt-tip pen.


## Összekötés




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:  
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm<sup>2</sup> (6 AWG) to 6 mm<sup>2</sup> (10 AWG) or from 6 mm<sup>2</sup> (10 AWG) to 2.5 mm<sup>2</sup> (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:  
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm<sup>2</sup> (6 AWG) and 10 mm<sup>2</sup> (8 AWG) and one cross-section size for 6/4/2.5 mm<sup>2</sup> (10/12/14 AWG). An example: from 16 mm<sup>2</sup> (6 AWG) to 6 mm<sup>2</sup> (10 AWG) (see illustration above) or from 10 mm<sup>2</sup> (8 AWG) to 4 mm<sup>2</sup> (12 AWG).



Note:  
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.