



Elektromos adatok

Minősítés az IEC/EN 60664-1 szerint

| | |
|-------------------------------|-------|
| Névleges feszültség (III / 3) | 800 V |
| Névleges áram | 57 A |

Robbanásvédelmi információk

| | |
|-------------------------|------|
| Névleges áram (Ex e II) | 50 A |
|-------------------------|------|

Fizikai adatok

| | |
|-----------------------|----------------------|
| Szélesség | 17,5 mm / 0.689 inch |
| Magasság | 4,1 mm / 0.161 inch |
| Mélység | 23 mm / 0.906 inch |
| Cellaáthidaló osztása | 2 ágú |

Anyag információk

| | |
|----------------------|----------------------------------------------------------------|
| Note (material data) | Information on material data can be found here |
| Szín | világosszürke |
| Tűzterhelés | 0.016 MJ |
| Tömeg | 3.9 g |

Kereskedelmi adatok

| | |
|--------------------|---------------|
| Product Group | 22 (TOPJOB S) |
| eCl@ss 10.0 | 27-14-11-40 |
| eCl@ss 9.0 | 27-14-11-40 |
| ETIM 8.0 | EC000489 |
| ETIM 7.0 | EC000489 |
| Csomagolási egység | 25 Stück |
| Csomagolás típusa | Bag |
| Származási ország | DE |
| EAN/VTSZ | 4055143701938 |
| Vámtarifaszám | 85366990990 |

Letöltések

Environmental Product Compliance


Compliance Search

Environmental Product Compliance 2010-402



Documentation

Additional Information

| | | |
|-------------------|-------------------|-------------------------------------------------------------------------------------|
| Technical Section | pdf 2142.18 KB |  |
|-------------------|-------------------|-------------------------------------------------------------------------------------|

Bid Text



| | | | |
|----------|------------|-----------------|---------------------------------------------------------------------------------------|
| 2010-402 | 28.04.2017 | doc 23.50 KB |  |
| 2010-402 | 19.02.2019 | xml 2.51 KB |  |

CAD/CAE-Data

| CAD data | CAE data |
|---------------------------------------|--------------------------------------------|
| 2D/3D Models 2010-402 | EPLAN Data Portal 2010-402 |
| | WSCAD Universe 2010-402 |
| | ZUKEN Portal 2010-402 |

Szerelési útmutató


Összekötés



Insert push-in type jumper bar and push down until it hits backstop.

Removing a push-in type jumper bar: Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper. Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.




Összekötés



Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).

Marking with a felt-tip pen.

Összekötés



Stepping down via push-in type jumper bar.

Stepping down via push-in type jumper bar: Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).

Stepping down via push-in type jumper bar: Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).

Note: The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.