



Elektromos adatok

Minősítés az IEC/EN 60664-1 szerint

Névleges feszültség (III / 3)	800 V
Névleges áram	32 A

Robbanásvédelmi információk

Névleges áram (Ex e II)	30 A
-------------------------	------

Fizikai adatok

Szélesség	29 mm / 1.142 inch
Magasság	4,1 mm / 0.161 inch
Mélység	19 mm / 0.748 inch
Cellaáthidaló osztása	5 ágú

Anyag információk

Note (material data)	Information on material data can be found here
Szín	világosszürke
Tűzterhelés	0.019 MJ
Tömeg	3.7 g

Kereskedelmi adatok

Product Group	22 (TOPJOB S)
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 8.0	EC000489
ETIM 7.0	EC000489
Csomagolási egység	25 Stück
Csomagolás típusa	Bag
Származási ország	DE
EAN/VTSZ	4055143699891
Vámtarifaszám	85366990990

Letöltések

Environmental Product Compliance


Compliance Search

Environmental Product Compliance 2004-405



Documentation

Additional Information

Technical Section	pdf 2142.18 KB	
-------------------	-------------------	---

Bid Text


2004-405	19.02.2019	xml 2.51 KB	
2004-405	28.04.2017	doc 23.50 KB	

CAD/CAE-Data


CAD data	CAE data
2D/3D Models 2004-405	EPLAN Data Portal 2004-405
	WSCAD Universe 2004-405
	ZUKEN Portal 2004-405

Szerelési útmutató

Összekötés



Insert push-in type jumper bar and push down until it hits backstop.




Removing a push-in type jumper bar: Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper. Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Összekötés



Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.

Összekötés




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar: Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar: Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note: The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.